



Install OPOS Driver

This section is dedicated to guiding you through the setup process of OPOS Printer.

ADD T-88 to OPOS

 If the screen below is not already open go to start > programs > OPOS > SetupPOS ver 2.00



- 2. Right Click POSPrinter
- 3. Click Add New Device



4. Select you device the TM-T88 and version number then select the detailed model. Also add a LDN of **EPSONPOS**

Please Note **USB** models will end with a **U** Please Note **COM** models will not have a trailing letter Please Note **LPT** models will end with a **P**

Display Ver1.xx	Display Ver2.xx	 TM-T88IIIU Used Port 	<u> </u>
Display Ver1.xx	Display Ver2.xx	Used Port	
		xx Used Port	
Device Description		USB	
EPSON TM-T88IIIL	J POS Printer		
INF File Name.		12	
C:\PROGRA~1\0F	POS\Epson2\PpT883.INF	Browse	
Set up a logical de * A logical device A logical device And, a logical de EPSONPOS	vice name if necessary. name isn't indispensable. name isn't set up in the case <u>vice name can be set up ev</u>	e as the blank. ven later.	

5. Make sure printer is connected and click next

	USB1	Port is being used by	
	Auto Settings	(None)	_
Setup of details	of the port.		
Baud <u>R</u> ate	<u>v</u>	InputBut	
BilLength	*	@utputBuf	
Parity		Output Interval Time	2500 msec
StopBit	×	Input SleepTime	msec
Handshake	<u> </u>		
Chack	Health Interactive	Denice Spec	ilio Settings

- Click Check Health Interactive then start.
 If you receive an error, click back and check you have the right printer.
 Also check the printer is properly connected
 If you get a test print prompt, click Next