ZEBRA TLP LABEL PRINTER SETUP GUIDE – VISTA





- 1. Have PC turned on, ensuring no programs are running.
- 2. Plug power into ZEBRA TLP and turn on by holding the round green button.
- 3. Plug USB lead into available USB port.
- 4. Vista will detect the device and prompt for further action (left)
- 5. Select " Don't show this message again for this device"

 Now you will be looking at a clear desktop. Click Start, then control panel.

7. Now in control panel, click Printers

| C C Views ✓ C Add a printer C | Now in the printer dialogue, select the "Add a printer" button. |
|--|--|
| Favorite Links Name Documents Status Comments >> Pictures Music Recently Changed Searches Public Image: Comment in the second seco | |
| Add Printer Choose a local or network printer Add a local printer | 9. The Add printer option will appear. 10. Simply select the "Add a local printer" option. 11. Then click next. |
| Add a network, wireless or Bluetooth printer Make sure that your computer is connected to the network, or that your Bluetooth or wireless printer is turned on. | |
| [jet] | |
| Add Printer Add Printer Choose a printer port A printer port is a type of connection that allows your computer to exchange information with a printer. UPT1: (Printer Port) UPT1: (Printer Port) UPT2: (Printer Port) UPT3: (Printer Port) U | You will now be looking at the printer selection pane. Ensure that "Use an existing port" is selected. Select the USB (Virtual Printer Port for USB)in the port selection box (right) Click Next. |
| COM3: (Serial Port) COM4: (Serial Port) FILE: (Print to File) (\systest01\Samsungs (Local Port) \Systest01\Samsungs (Local Port) Desktop\",pdf (Adobe PDF Port) Desktop\",pdf (Adobe PDF Port) USB001 (Virtual printer port for USB) XPSPort: (Local Port) Next Cancel | |

